

R1-E.354-G10

| CFM | Static Pressure in Inches W.G. | | | | |
|------|--------------------------------|-------------|-------------|-------------|-------------|
| | 0.000 | 0.250 | 0.500 | 0.750 | 1.000 |
| | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP |
| 1200 | 905 / 0.11 | 1061 / 0.18 | 1263 / 0.30 | 1485 / 0.49 | 1697 / 0.73 |
| 1400 | 1055 / 0.18 | 1183 / 0.25 | 1344 / 0.36 | 1527 / 0.53 | 1716 / 0.76 |
| 1600 | 1206 / 0.26 | 1315 / 0.34 | 1445 / 0.45 | 1595 / 0.61 | 1758 / 0.81 |
| 1800 | 1356 / 0.37 | 1452 / 0.46 | 1561 / 0.57 | 1685 / 0.72 | 1824 / 0.91 |
| 2000 | 1507 / 0.51 | 1591 / 0.60 | 1686 / 0.72 | 1792 / 0.86 | |
| 2200 | 1658 / 0.68 | 1734 / 0.78 | 1817 / 0.90 | | |
| 2400 | 1809 / 0.88 | 1876 / 0.99 | | | |

Max Sizeable RPM = 1884 RPM. Table shown extended beyond this point for reference only.

Motor BMN48-750I2-50-230/277 has an rpm range of 900 to 1800.

Motor BMN48-750I2-60-230/277 has an rpm range of 900 to 1800.

Motor M055PWCUK0315-ECM-50-115 has an rpm range of 900 to 1800.

Motor M055PWCUK0315-ECM-50-230 has an rpm range of 900 to 1800.

Motor M055PWCUK0315-ECM-60-115 has an rpm range of 900 to 1800.

Motor M055PWCUK0315-ECM-60-230 has an rpm range of 900 to 1800.